

APPENDIX II B

Instruction Codes of Intel 8085 in Hexadecimal Order

Hex Code	Mnemonic		Hex Code	Mnemonic	
00	NOP		27	DAA	
01	LXI	B	29	DAD	H
02	STAX	B	2A	LHLD	
03	INX	B	2B	DCX	H
04	INR	B	2C	INR	L
05	DCR	B	2D	DCR	L
06	MVI	B	2E	MVI	L
07	RLC		2F	CMA	
09	DAD	B	30	SIM	
0A	LDAX	B	31	LXI	SP
0B	DCX	B	32	STA	
0C	INR	C	33	INX	SP
0D	DCR	C	34	INR	M
0E	MVI	C	35	DCR	M
0F	RRC		36	MVI	M
11	LXI	D	37	STC	
12	STAX	D	39	DAD	SP
13	INX	D	3A	LDA	
14	INR	D	3B	DCX	SP
15	DCR	D	3C	INR	A
16	MVI	D	3D	DCR	A
17	RAL	D	3E	MVI	A
19	DAD	D	3F	CMC	
1A	LDAX	D	40	MOV	B, B
1B	DCX	D	41	MOV	B, C
1C	INR	E	42	MOV	B, D
1D	DCR	E	43	MOV	B, E
1E	MVI	E	44	MOV	B, H
1F	RAR		45	MOV	B, L
20	RIM		46	MOV	B, M
21	LXI	H	47	MOV	B, A
22	SHLD		48	MOV	C, B
23	INX	H	49	MOV	C, C
24	INR	H	4A	MOV	C, D
25	DCR	H	4B	MOV	C, E
26	MVI	H			

Hex Code	Mnemonic	Hex Code	Mnemonic
4C	MOV C, H	78	MOV A, B
4D	MOV C, L	79	MOV A, C
4E	MOV C, M	7A	MOV A, D
4F	MOV C, A	7B	MOV A, E
50	MOV D, B	7C	MOV A, H
51	MOV D, C	7D	MOV A, L
52	MOV D, D	7E	MOV A, M
53	MOV D, E	7F	MOV A, A
54	MOV D, H	80	ADD B
55	MOV D, L	81	ADD C
56	MOV D, M	82	ADD D
57	MOV D, A	83	ADD E
58	MOV E, B	84	ADD H
59	MOV E, C	85	ADD L
5A	MOV E, D	86	ADD M
5B	MOV E, E	87	ADD A
5C	MOV E, H	88	ADC B
5D	MOV E, L	89	ADC C
5E	MOV E, M	8A	ADC D
5F	MOV E, A	8B	ADC E
60	MOV H, B	8C	ADC H
61	MOV H, C	8D	ADC L
62	MOV H, D	8E	ADC M
63	MOV H, E	8F	ADC A
64	MOV H, H	90	SUB B
65	MOV H, L	91	SUB C
66	MOV H, M	92	SUB D
67	MOV H, A	93	SUB E
68	MOV L, B	94	SUB H
69	MOV L, C	95	SUB L
6A	MOV L, D	96	SUB M
6B	MOV L, E	97	SUB A
6C	MOV L, H	98	SBB B
6D	MOV L, L	99	SBB C
6E	MOV L, M	9A	SBB D
6F	MOV L, A	9B	SBB E
70	MOV M, B	9C	SBB H
71	MOV M, C	9D	SBB L
72	MOV M, D	9E	SBB M
73	MOV M, E	9F	SBB A
74	MOV M, H	A0	ANA B
75	MOV M, L	A1	ANA C
76	HLT	A2	ANA D
77	MOV M, A	A3	ANA E

Hex Code	Mnemonic	Hex Code	Mnemonic
A4	ANA H	D1	POP D
A5	ANA L	D2	JNC
A6	ANA M	D3	OUT
A7	ANA A	D4	CNC
A8	XRA B	D5	PUSH D
A9	XRA C	D6	SUI
AA	XRA D	D7	RST 2
AB	XRA E	D8	RC
AC	XRA H	DA	JC
AD	XRA L	DB	IN
AE	XRA M	DC	CC
AF	XRA A	DE	SBI
B0	ORA B	DF	RST 3
B1	ORA C	E0	RPO
B2	ORA D	E1	POP H
B3	ORA E	E2	JPO
B4	ORA H	E3	XTHL
B5	ORA L	E4	CPO
B6	ORA M	E5	PUSH H
B7	ORA A	E6	ANI
B8	CMP B	E7	RST 4
B9	CMP C	E8	RPE
BA	CMP D	E9	PCHL
BB	CMP E	EA	JPE
BC	CMP H	EB	XCHG
BD	CMP L	EC	CPE
BE	CMP M	EE	XRI
BF	CMP A	EF	RST 5
C0	RNZ	F0	RP
C1	POP B	F1	POP PSW
C2	JNZ	F2	JP
C3	JMP	F3	DI
C4	CNZ	F4	CP
C5	PUSH B	F5	PUSH PSW
C6	ADI	F6	ORI
C7	RST 0	F7	RST 6
C8	RZ	F8	RM
C9	RET	F9	SPHL
CA	JZ	FA	JM
CC	CZ	FB	EI
CD	CALL	FC	CM
CE	ACI	FE	CPI
CF	RST 1	FF	RST 7
D0	RNC		

Total Mnemonics = 246.